

# Software Design Specification

# Z-Wave Plus Role Type Specification

Description:	This document defines the Z-Wave Plus Role Types, which specify how a Z-Wave Plus node must react from a network perspective.
Written By:	Z-Wave Alliance
Date:	2021.03.18
Reviewed By:	AWG
Restrictions:	Public

#### Approved by:

Z-Wave Alliance Board of Directors

THIS SPECIFICATION IS BEING OFFERED WITHOUT ANY WARRANTY WHATSOEVER, AND IN PARTICULAR, ANY WARRANTY OF NON-INFRINGEMENT IS EXPRESSLY DISCLAIMED. ANY USE OF THIS SPECIFICATION SHALL BE MADE ENTIRELY AT THE IMPLEMENTER'S OWN RISK, AND NEITHER THE ALLIANCE, NOR ANY OF ITS MEMBERS OR SUBMITTERS, SHALL HAVE ANY LIABILITY WHATSOEVER TO ANY IMPLEMENTER OR THIRD PARTY FOR ANY DAMAGES OF ANY NATURE WHATSOEVER, DIRECTLY OR INDIRECTLY, ARISING FROM THE USE OF THIS SPECIFICATION.

	REVISION RECORD							
Doc. Ver.	Date	Ву	Pages affected	Brief description of changes				
13	20160823	JFR	All	Prepared for Public Z-Wave initiative				
14	20161020	NOBRIOT	3.3.2 5.9	Integrated approved contents from the 2016C contributions <ul> <li>Added Security 2 controller bootstrapping requirements</li> <li>Added the NAS Role Type</li> </ul>				
15	20170102	NOBRIOT	Error! Reference source not found. 3.3.2 0 RT sections	<ul> <li>Integrated approved contents from the 2016D contributions:</li> <li>Updated the Encapsulation order figure</li> <li>Added a clarification about the default S2 key granting</li> <li>Clarified requirements for the Wake Up mechanism</li> <li>Changed Lifeline configuration recommendations when a controller is not the SIS, due to the new Inclusion Controller Command Class</li> </ul>				
16	20170402	NOBRIOT	3.3.1 0 4 RT Sections 5.1, 5.2, 5.3 & 5.4	<ul> <li>Integrated approved contents from the 2017A contributions</li> <li>Clarified what is allowed when S0 bootstrapping fails for S0 capable controllers.</li> <li>Clarified the "heartbeat communication" is actually intended to described Wake-Up Notification mechanism only</li> <li>Added Commissioning and Runtime phase definitions</li> <li>Removed/updated the Wake-Up configuration requirements for inclusion controllers due to the new Inclusion Controller CC.</li> <li>Changed Lifeline/Wake-up recommendations for inclusion controllers to reflect the new S2 Inclusion Controller frame flow.</li> <li>Moved Lifeline association group section to [1]</li> </ul>				
17	20170702	NOBRIOT	3.3.2.1 3.4 Table 1 RT Sections 5.1.2.4 & 5.2.2.4 Appendix A.1 3.10	<ul> <li>Integrated approved content from the 2017B contributions</li> <li>Removed optional statements and clarified S2 bootstrapping</li> <li>Removed redundant requirement for the Device Reset Locally Command Class</li> <li>Removed "MUST support Security" from the Role Type Overview</li> <li>(Re-)Added mains/battery and listening flag requirements in every Role Type</li> <li>Clarified that optional Wake Up Interval Set Command must contain the SIS' NodeID.</li> <li>Updated Learn Mode recommended diagram</li> <li>Added SmartStart requirements</li> </ul>				
18 19	20170711 20171002	NOBRIOT	3.10 3.3.2.3 3.10.2.2 5.1.2.7 3.3.1 3.10	Added SmartStart controller requirements         Integrated approved content from the 2017C contributions:         • Clarifications about S2 and informing the end user about security         • Minor edits about Node Provisioning requirements         • Rephrasing Lifeline requirement in CSC Role Type definition         Added clarification for S0 bootstrapping with/without Inclusion Controller         Command Class         Updated some SmartStart requirements				

REVISION RECORD						
Doc. Ver.	Date	Ву	Pages affected	Brief description of changes		
20	20180110	NOBRIOT	Table 2 Error! Reference source not found. 3.10 5.3, 5.4, 5.5, 5.7 & 5.8	<ul> <li>Integrated approved content from the 2017D contributions:</li> <li>Fixed an error in the Role Type identifiers</li> <li>Added requirement for controllers to generate HomeIDs with a random number generator</li> <li>Short clarifications to SmartStart requirements</li> <li>Added Command Class support requirements (Wake Up and Battery) in Role Type definitions</li> </ul>		
21	20180305	BBR	All	Added Silicon Labs template		
22	20180404	NOBRIOT	5.1.2.7 3.5 3.10.2.2 5	<ul> <li>Integrated approved content from the 2018A contributions:</li> <li>Removed requirement for CSC to establish Lifeline to an including RPC.</li> <li>Added node interview response timeout recommendations</li> <li>Clarified text for "classic" inclusion</li> <li>Updated network inclusion, bootstrapping and interview description</li> </ul>		
23	20180701	NOBRIOT	3.4 5.1.2.4 & 5.2.2.4 3.3.1.1	<ul> <li>2018B Contributions:</li> <li>Added requirements and guidelines for device reset</li> <li>Relaxed Wake-Up Interval value requirements for PS Role Type</li> <li>Added Security 0 recommendations</li> </ul>		
24	20181001	NOBRIOT	5.1	Contributions 2018C: - Changed the Replaced Failing Node functionality optional for the CSC Role Type		
25	20190101	DEWASSIE NOBRIOT	3.2 3.3.2.3 3.10.2.2 5.1.2.6	<ul> <li>Contributions 2018D:</li> <li>Added failed node Remove and Replace functionalities and updated Learn Mode and Add Mode descriptions and requirements</li> <li>Added end user notification requirements when user interface is not active during S2 bootstrapping</li> <li>Removed edit requirement in the Node Provisioning List</li> <li>Clarified that Replace Failing Node is always optional</li> </ul>		
26	20190401	NOBRIOT	3.3.2.1	Contributions 2019A: • Made CSA support in S2 optional for SIS controllers having the SIS role.		
27	20190701	NOBRIOT	3.3.2.3 3.8.1 5.1, 5.2, 5.3 & 5.4	<ul> <li>Contributions 2019B:</li> <li>Made end-user instructions optional in case of S2 timeout waiting for the SIS.</li> <li>Allowed controller nodes to skip transmission attempts to non-existing NodelDs.</li> <li>Reorganized the Lifeline requirements for each controller Role Type into a single section, not depending on the Role Type being included</li> </ul>		
28	20200101	DEWASSIE	3.2 3.3.1	<ul> <li>Contributions 2019D:</li> <li>Added a requirement for the SIS to show nodes added by the Inclusion Controller</li> <li>Added a requirement regarding the SIS not to perform the S0 bootstrapping in inclusion controller scenario</li> </ul>		

REVISION RECORD						
Doc. Ver.	Date	Ву	Pages affected	Brief description of changes		
29	20200701	NOBRIOT DEWASSIE	5.1.1 3.8.2 3.10.2.1	<ul> <li>Contributions 2020A:</li> <li>Made learn mode optional for CSC Role Type.</li> <li>Updated the stay awake requirement, restricting which frames let a node stay awake.</li> <li>Relaxed the Node Provisioning support requirement by Z/IP Gateway.</li> </ul>		
30	20200901	NOBRIOT	Chapter 3 5.1.2.4 & 5.2.2.4	<ul> <li>Contributions 2020B:</li> <li>Removed all definitions and requirements covered by the Z-Wave Network Layer specification (replaced by [12])</li> <li>Removed encapsulation order overview (duplicate from [5])</li> <li>Removed the MAY statement for input methods supporting different key classes for inclusion controllers and primary controllers.</li> <li>Removed Wake Up requirement for the PS Role Type.</li> </ul>		
30	2021.03.18	ZWA Board		Approved for Publication		

# **Table of Contents**

1	ABBREVIATIONS	1
2	INTRODUCTION	2
2.1	Purpose	2
2.2	Precedence of definitions	2
2.3	Terms used in this document	2
3	Z-WAVE COMPLIANCE OVERVIEW	3
3.1	SIS assignment	3
3	.1.1 Non-SIS capable Primary Controllers	3
3	.1.2 SIS capable controllers	3
3	.1.3 SIS return route assignment	3
3.2	Network Inclusion and exclusion	3
3.3	Security bootstrapping	4
3	.3.1 Security 0 Command Class	4
	3.3.1.1 Upgrading non-secure networks	4
3	.3.2 Security 2 Command Class	4
	3.3.2.1 Bootstrapping capabilities	4
	3.3.2.2 Granting Security Classes	5
	3.3.2.3 Informing the user about security	5
3.4	Device Reset Locally support	6
3.5	Node interview and response timeouts	6
3.6	Polling Devices	8
3	.6.1 Polling with no errors	8
3	.6.2 Polling with transmit error	9
3	.6.3 Polling with missing Report frame.	11
3.7	Unsolicited communication	12
3.	.7.1 Unsolicited data collection communication	12
3.	.7.2 Unsolicited control communication	12
3.8	Runtime communication	13
3	.8.1 Routing	13
3	.8.2 Wake-Up communication timeout protection	14
3.9	Network maintenance	15
3.10	0 SmartStart requirements	16
3	.10.1 Support requirements	16
	3.10.1.1 SmartStart learn mode activation	16
2	3.10.1.2 Figner inclusion Request InterVal	16
3.	2 10 2 1 Command Class support	10
	2.10.2.1 Command Class Support	10
	3.10.2.2 USEI III.eliace	16 47
		1/

 $\ensuremath{\mathbb{C}}$  2021 Z-Wave Alliance, Inc. All Rights Reserved. This document may only be copied and distributed internally.

4	ROLE	TYPE OVERVIEW	18
4.1	Deteo	cting the Role Type of a device	19
5	ROLE	TYPE DEFINITIONS	20
5 1	Conti	ral Static Controller (CSC)	22
5.1	1 1	CSC Protocol Requirements	22 22
5	. ı. ı 5 1 1 1	If first node in the network	22
5	1.2	CSC Setun	22
Ŭ	5121	Inclusion process	22
	5122	l ifeline configuration	22
	5.1.2.3	CSC including a SSC. PC. RPC or NAS	23
	5.1.2.4	CSC including a PS. LSS or RSS	23
	5.1.2.5	5 CSC including an AOS	23
	5.1.2.6	CSC including another CSC	24
	5.1.2.7	CSC included by a PC, RPC, SSC	24
5	.1.3	CSC Runtime Configuration	24
5	.1.4	CSC Runtime Communication	24
5.2	Sub S	Static Controller (SSC)	25
5	.2.1	SSC Protocol Requirements	25
	5.2.1.1	If first node in the network	25
5	.2.2	SSC Setup	25
	5.2.2.1	Inclusion process	25
	5.2.2.2	2 Lifeline configuration	25
	5.2.2.3	3 SSC including a CSC	26
	5.2.2.4	SSC including an RPC, PS or RSS	26
	5.2.2.5	5 SSC including an SSC, PC, AOS, LSS or NAS	26
5	.2.3	SSC Runtime Configuration	26
5	.2.4	SSC Runtime communication	27
5.3	Porta	able Controller (PC)	28
5	.3.1	PC Protocol Requirements	28
	5.3.1.1	If first node in the network	28
5	.3.2	PC Setup	28
	5.3.2.1	Inclusion process	28
	5.3.2.2	2 Lifeline configuration	28
	5.3.2.3	B PC including a CSC	29
	5.3.2.4	PC including an RPC, PS or RSS	29
_	5.3.2.5	5 PC including an SSC, PC, AOS, LSS or NAS	29
5	.3.3	PC Runtime Configuration	29
5	.3.4	PC Runtime communication	29
5.4	Repo	Drung Portable Controller (RPC)	30
5	.4.1	KPC Protocol Requirements	30
-	5.4.1.1	IT TIRST NODE IN THE NETWORK	30
5	.4.2		30
	<b>b.4.2.1</b>	inclusion process	30

 $\ensuremath{\mathbb{C}}$  2021 Z-Wave Alliance, Inc. All Rights Reserved. This document may only be copied and distributed internally.

Page vi of viii

5.4.2.2	Lifeline configuration	30
5.4.2.3	RPC including a CSC	31
5.4.2.4	RPC Including an RPC, PS or RSS	31
5.4.2.5	RPC including an SSC, PC, AOS, LSS or NAS	31
5.4.3	RPC runtime configuration	31
5.4.4	RPC runtime communication	31
5.5 Porta	able Slave (PS)	32
5.5.1	PS Protocol Requirements	32
5.5.2	PS Setup	32
5.5.2.1	Inclusion process	32
5.5.3	PS Runtime configuration	32
5.5.4	PS Runtime communication	32
5.6 Alwa	ys On Slave (AOS)	33
5.6.1	AOS Protocol Requirements	33
5.6.2	AOS Setup	33
5.6.2.1	Inclusion process	33
5.6.3	AOS Runtime Configuration	33
5.6.4	AOS Runtime communication	33
5.7 Repo	orting Sleeping Slave (RSS)	34
5.7.1	RSS Protocol Requirements	34
5.7.2	RSS Setup	34
5.7.2.1	Inclusion process	34
5.7.3	RSS Runtime configuration	34
5.7.4	RSS Runtime communication	34
5.8 Liste	ning Sleeping Slave (LSS)	35
5.8.1	LSS Protocol Requirements	35
5.8.2	LSS Setup	35
5.8.2.1	Inclusion process	35
5.8.3	LSS Runtime configuration	35
5.8.4	LSS Runtime communication	35
5.9 Netw	ork Aware Slave (NAS)	36
5.9.1	NAS Protocol Requirements	36
5.9.2	NAS Setup	36
5.9.2.1	Inclusion process	36
5.9.3	NAS Runtime Configuration	36
5.9.4	NAS Runtime communication	36
REFEREN	CES	

# **Table of Figures**

Figure 1, Node interview ReportTime timeout without security	7
Figure 2, Node interview ReportTime timeout with security	7
Figure 3, Polling (No errors, without security)	9
Figure 4, Polling (No errors, with security)	9
Figure 5, Polling (No Ack, without security)	10
Figure 6, Polling (No Ack, with security 0)	10
Figure 7, Polling (No Report frame, without security)	11
Figure 8, Polling (No Report frame, with security)	11
Figure 9, Successful transmission using last working routes	
Figure 10, Successful transmission using Explorer Frame	
Figure 11, Unsuccessful transmission	14
Figure 12, Wake Up Command Class	15
Figure 13, Node Setup / commissioning	20
Figure 14, Inclusion process for the node being included	
Figure 15, Inclusion process for the including node	

# Table of Tables

Table 1, Overview of Role Types	18
Table 2, Role Type identifiers	19

# **1** ABBREVIATIONS

Abbreviation	Explanation
AOS	Always On Slave
AGI	Association Group Information
CSC	Central Static Controller
DT	Device Type
NAS	Network Aware Slave
NIF	Node Information Frame
PC	Portable Controller
RPC	Reporting Portable Controller
PS	Portable Slave
LSS	Listening Sleeping Slave
SDK	Software Developer's Kit
SIS	SUC (Node) ID Server
RSS	Reporting Sleeping Slave
SSC	Sub Static Controller
SUC	Static Update Controller
NOP	No Operation

## 2 INTRODUCTION

#### 2.1 Purpose

This document describes the Z-Wave Plus Role Types. The purpose of the Role Type is to provide a high level definition of how Z-Wave nodes must react from a Z-Wave networking perspective.

This document is not meant to be read in full. It is aimed at being a scalable documentation process for network specific functionality for various Z-Wave devices. It should be read together with the Device Type specification [1], which highlights what Role Types should be used for different Device Types. A device will typically have one Role Type associated with it, but in some cases there can be more than one. The developer now only needs to look at one Role Type to determine the implementation of the network specific functionality to pass certification.

It is however necessary to understand how the Central Static Controller (CSC) works as most devices will heavily depend on it for direct communication.

#### 2.2 Precedence of definitions

In terms of reviewing products for Z-Wave Plus Compliance, definitions in this document have precedence over the files distributed as part of the Software Developer's Kit (SDK). However, assignments of identifiers for all Role Types, Device Types, Device Classes and Command Classes are located in [8].

Role Type, Device Type and Command Class Specifications approved as a final version during the Type/Class development process have precedence over this document temporarily until integrated into this document.

#### 2.3 Terms used in this document

The key words "MUST", "MUST NOT", "REQUIRED", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document MUST be interpreted as described in IETF RFC 2119 [7].

## **3 Z-WAVE COMPLIANCE OVERVIEW**

The following sections present Z-Wave properties applying to all Z-Wave Plus Role Types defined in this document. Requirements presented in this chapter MUST be respected by all Z-Wave Plus devices.

#### 3.1 SIS assignment

#### 3.1.1 Non-SIS capable Primary Controllers

A Z-Wave network may have no SIS capable controller. For instance this is the case if the network consists of a Portable Controller (PC) which is used to include a number of Always On Slaves (AOS). In this case, the PC acts as the Primary Controller.

RT:00.11.0006.2 If no SIS is present in the network, when including a controller supporting SIS functionality, a non-SIS capable Primary Controller MUST assign the SIS role to the newly included controller.

#### **3.1.2** SIS capable controllers

- RT:00.11.0007.2 All controllers that support the SIS functionality MUST accept to become SIS upon request from a Primary Controller.
- RT:00.11.0008.2 A controller that supports SIS functionality MUST assume the SIS role when creating a new network.

#### 3.1.3 SIS return route assignment

RT:00.11.0009.1 When the SIS is present, an including node MUST always assign SIS return route when including a slave node.

#### 3.2 Network Inclusion and exclusion

#### Learn Mode:

RT:00.11.000A.1 A Z-Wave Plus compliant node MUST support both Classic and Network Wide Inclusion (NWI).

Appendix A outlines the inclusion process.

#### Add Mode:

Add mode is used by a controller for including a new node to a network.

RT:00.11.003E.2 The SIS MUST show the new added nodes in the list of included nodes after an inclusion has been carried out by an Inclusion Controller.

#### 3.3 Security bootstrapping

#### 3.3.1 Security 0 Command Class

RT:00.21.0001.1 Controllers MUST be able to perform Security 0 bootstrapping if they support the Security 0 Command Class. Refer to [1].

# If a controller has the Inclusion Controller role in a network and includes a node that supports Security 0RT:00.21.0002.1Command Class only (i.e. does not support Security 2 Command Class), it MUST perform Security 0<br/>bootstrapping immediately after including the node.

If the SIS and the Inclusion Controller both support the Inclusion Controller Command Class, theRT:00.21.0003.1inclusion controller MUST NOT perform S0 bootstrapping unless instructed by the SIS with an Inclusion<br/>Controller Initiate Command (S0\_INCLUSION).

- RT:00.21.0005.1 If the SIS and the Inclusion Controller both support the Inclusion Controller Command Class, the SIS MUST NOT perform S0 bootstrapping. The SIS should instruct the Inclusion Controller to perform S0 bootstrapping or interview the included node non-securely.
- RT:00.21.0004.1 If an error happens during SO bootstrapping of an SO capable controller, the included controller MAY refuse to provide network functions (others than Learn Mode). In this case, the included controller MUST indicate to the user that it needs to be excluded and re-included in the Z-Wave network.

#### 3.3.1.1 Upgrading non-secure networks

RT:00.23.0001.1 If a controller is included in a non-secure network as an inclusion controller, it MAY start using its own S0 network key and perform S0 bootstrapping with newly included nodes.

A controller MUST NOT start using its own S0 network key if S0/S2 bootstrapping failed

#### 3.3.2 Security 2 Command Class

The following sections describe requirements for controllers supporting Security 2 Command Class

#### 3.3.2.1 Bootstrapping capabilities

Security 2 mandates certain functionalities depending on the controller's role in the network.

If a controller has the SIS role:

RT:00.21.0006.1

RT:00.21.0007.1

RT:00.21.0008.1

RT:00.21.0009.1

RT:00.23.0006.1

- It MUST support the SIS side of the Inclusion Controller Command Class
- It MUST perform Security 2 bootstrapping.
- It MUST support inclusion of nodes that implement any combination of Security 2 Security Classes
- It MUST have input and display method for support of all Security Classes.
- It MAY support inclusion using CSA

© 2021 Z-Wave Alliance, Inc. All Rights Reserved. This document may only be copied and distributed internally.

Z-Wave Plus Role Type Specification If a controller has the Inclusion Controller role: It MUST support the Inclusion Controller side of the Inclusion Controller Command Class RT:00.21.000A.1 It MUST NOT perform Security 2 bootstrapping RT:00.21.000B.1 If a controller has the Primary Controller role: RT:00.23.0003.1 It MAY perform Security 2 bootstrapping 3.3.2.2 **Granting Security Classes** A controller with a user interface for PIN code input (and optionally a QR scanning capability) MUST RT:00.21.000C.1 comply with following when bootstrapping S2 nodes: It MUST grant membership of all requested Classes if the joining node requests membership of the S2 Access Control Class (unless specified otherwise by a user). It MAY ask the user for confirmation before granting S2 Authenticated Class key if the node does not request membership of the S2 Access Control Class. It SHOULD provide a way to inspect and adjust the list of the Security Class memberships that ٠ will be granted to the joining node A constrained controller with no QR scanning capability and no user interface for PIN code input MUST RT:00.21.000D.1 comply with following when bootstrapping S2 nodes: It MUST grant membership of the S2 Unauthenticated Class if the joining node requests • membership of the S2 Unauthenticated Class. It MUST abort the S2 bootstrapping entirely (grant no key) if the joining node does not request • membership of the S2 Unauthenticated Class. 3.3.2.3 Informing the user about security If a node has been security bootstrapped with the S0 Command Class in a S2 capable network, the SIS/Primary controller MUST issue a warning message to the user informing that the node has not been RT:00.21.000E.1 included securely. The SIS/Primary controller SHOULD request a new NIF to the included node after RT:00.22.0001.1 security bootstrapping to verify if the included node supports S2 before issuing the message to the user. This is made to ensure that the end user is aware of which security level a node has been bootstrapped and therefore identify if a S0 downgrade attack took place during bootstrapping or if a non-S2 inclusion controller bootstrapped the joining node. If an S2 node has not been granted the highest requested S2 key during bootstrapping, the SIS/Primary RT:00.21.000F.1 controller MUST issue a warning message to the user informing that the node has not been included with the highest security. This is OPTIONAL if the user has actively chosen which keys to grant and security bootstrapping completed successfully. In an Inclusion Controller scenario, the SIS' UI may not be active during S2 bootstrapping. In this case, the following rules apply: If the SIS automatically grants unauthenticated key for a node that request S2 Unauthenticated • RT:00.23.0005.1 Class, it MAY notify the end user the next time it uses the UI.

	Z-Wave Plus Role Type Specification							
RT:00.22.0002.1	• If the SIS timed out during S2 bootstrapping, it SHOULD instruct the end user that the node needs to be excluded and re-included.							
	3.4 Device Reset Locally support							
RT:00.11.000B.1	If a device can be reset to factory default locally on the device, the device MUST be able to issue a Device Reset Locally Command via its Lifeline to notify the Lifeline destination that the device has been reset to its factory default state. The product documentation MUST include instructions on how to perform a reset to factory default operation.							
RT:00.11.000C.1	If a device cannot be locally (or manually) reset to factory default, the device MUST NOT implement the Device Reset Locally functionality and MUST NOT list the Device Reset Locally Command Class identifier in the NIF.							
RT:00.11.000D.1	If a device is reset, it MUST perform the reset operation regardless of whether the delivery of the Device Reset Locally Notification is successful or not.							
	It is RECOMMENDED that devices implement a mechanism that allows the user to determine when the reset operation is completed.							
	When a node is reset,							
RT:00.11.000E.1	• it MUST forget its current HomeID and consider itself excluded from the network.							
RT:00.13.0001.1	<ul> <li>The configuration of Application Command Classes [3] MAY stay unchanged (e.g. configuration parameters, Thermostat Setpoint, Clock, Door lock Timeout configuration, User codes,)</li> </ul>							
RT:00.11.000F.1	<ul> <li>The configuration of other Command Classes (Management [4], Transport [5] or network [6]) MUST be reset to default (i.e. S2 keys are forgotten, Associations and Wake-Up configurations are cleared, etc.)</li> </ul>							
	3.5 Node interview and response timeouts							
RT:00.11.0010.1	During a node capability discovery or interview, as well as traffic generated due to user activation, a controlling nodes MUST timeout waiting for responses (reports) as part of the capability discovery or controlling scenarios.							
	Two timers named CommandTime and ReportTime are used for timing out during a node discovery interview. Illustrations are given for secure and non-secure cases in Figure 1 and Figure 2							

• CommandTime is measured by the application

RT:00.12.0001.1

• ReportTime timeout SHOULD be set to CommandTime + 1 second.







Figure 2, Node interview ReportTime timeout with security

#### 3.6 Polling Devices

A controlling device may monitor nodes or issue requests for status information. Communication patterns include, but are not limited to, the transmission of a:

- No Operation (NOP) Command to verify that a node is operational
- Get Command requesting status information in a Report Command
- Set Command followed by a Get Command requesting status information in a Report Command
- RT:00.11.0011.1 Communication MUST be considered polling if a controlling device autonomously sends requests to one or more nodes in a repeating fashion to monitor nodes or to get information from nodes. This applies to any combination of commands.

Z-Wave is a radio technology with limited bandwidth. Therefore, it is NOT RECOMMENDED to use
 polling. If used, polling communication MUST comply with the requirements stated in the sections 3.6.1 through 3.6.3.

- RT:00.11.0013.1 Communication MUST NOT be considered as polling if:
  - A node issues one or more commands in a burst initiated by a user action. This applies to any combination of commands; also requests.
  - A node issues one or more commands initiated by the inclusion of another node. This applies to any combination of commands; also requests.

#### 3.6.1 Polling with no errors

Two timers named CommandTime and PollTime are used for polling requirements with no error. Illustrations are given for secure and non-secure cases in Figure 3 and Figure 4

The following requirements apply to the normal case where a polling request is successful.

- RT:00.11.0014.1 RT:00.11.0015.1 RT:00.12.0002.1 RT:00.11.0016.1
- CommandTime MUST be measured by the application
- The application MUST wait PollTime before polling any other node
- PollTime SHOULD be 10 seconds + CommandTime or more
- PollTime MUST NOT be less than 1 second + CommandTime



Z-Wave Plus Role Type Specification





Figure 4, Polling (No errors, with security)

#### 3.6.2 Polling with transmit error

Two timers named CommandTime and PollTime are used for polling requirements with transmission error. Illustrations are given for secure and non-secure cases in Figure 5 and Figure 6. Note that in the case of a missing Ack, the Sending node MUST transmit the Get Command 3 times before considering

the Ack to be missing. CommandTime is measured from the first Get Command transmission to the timeout.

The following requirements apply to the case where a polling request is not successful.

- RT:00.11.0018.1
- If the transmission fails, the application MUST wait PollTime before polling any other node. PollTime MUST be 10 seconds + CommandTime or more







Figure 6, Polling (No Ack, with security 0)

#### 3.6.3 Polling with missing Report frame.

Two timers named CommandTime and ReportTime are used for polling requirements when the transmission is successful but with missing report. Illustrations are given for secure and non-secure cases in Figure 7 and Figure 8

The following requirements apply to the case where a polling request is successful but no Report frame is received.

- The application MUST wait ReportTime for the reply from node X before polling any other node
- RT:00.11.0019.1 RT:00.11.001A.1
- ReportTime MUST be CommandTime + 10 seconds or more



Figure 7, Polling (No Report frame, without security)





#### 3.7 Unsolicited communication

A device MAY autonomously send control commands or status information in response to physical events or in response to a timer.

Unsolicited communication patterns include, but are not limited to, the transmission of a:

- Control command turning on light in response to a detected movement
- Power meter report sending a usage report

Different requirements apply to unsolicited data collection communication and unsolicited control communication, respectively.

#### 3.7.1 Unsolicited data collection communication

Bursts of one or more commands which carry status information transmitted repeatedly without any user intervention MUST be considered to be <u>unsolicited data collection communication</u>. Using the transmission of a control command or a NOP command as a heartbeat indication MUST also be considered unsolicited data collection communication.

RT:00.11.001C.1 To save bandwidth, data collection communication MUST comply with the following requirements.

- A device MAY issue unsolicited data collection communication in any burst size
- A device MUST NOT issue new unsolicited data collection communication less than 30 seconds since the last burst.

#### 3.7.2 Unsolicited control communication

RT:00.11.001D.1 Bursts of one or more control commands initiated by a user action, a physical event or a time trigger MUST be considered control communication. Control communication MUST comply with the following requirements:

- A device MAY issue unsolicited control communication in any burst size.
- A device MAY issue unsolicited control communication at any interval since the last burst

#### 3.8 Runtime communication

#### 3.8.1 Routing

RT:00.11.001E.1 A Z-Wave Plus node MUST use by default the last working route to communicate with a target node. An illustration is given in Figure 9



Figure 9, Successful transmission using last working routes

Over time, there is a risk that nodes are moved or stop working. To ensure that nodes adapt to RT:00.11.001F.1 changing network topology and failing repeaters, a Z-Wave Plus node MUST enable dynamic route resolution. Dynamic route resolution consists of trying the following routes:

- Last working routes
- Calculated routes
- Explorer Frame

#### Illustrations are given in Figure 10 and Figure 11



Figure 10, Successful transmission using Explorer Frame

- RT:00.11.0020.1 A node MUST perform 3 routing attempts based on last working routes and/or calculated routes before sending an Explorer Frame. As outlined in Figure 10, controllers may calculate routes using the local neighbor map.
- RT:00.13.0003.1 Listening Sleeping Slaves (LSS) and Reporting Sleeping Slaves (RSS) MAY use return routes injected by a controller. The outlined sequence of transmission attempts is handled entirely by the routing protocol.

In case the destination is not reachable, all routed transmission attempts will fail and ultimately, the routing protocol will have to give up delivering the frame. After a failed transmission, the application MAY try to transmit again in case a new event occurs, e.g. because the user issues a new button press.

The steps in Figure 11 involve at least three routing attempts. When all routing attempts are unsuccessful, it is very unlikely that any other transmission attempt to the same target will succeed. The sending node SHOULD give up the frame transmission.



#### Figure 11, Unsuccessful transmission

RT:00.13.0005.1 Nodes based on a controller role type MAY skip transmission attempts if they are associated to a nonexisting NodeID.

#### 3.8.2 Wake-Up communication timeout protection

A battery powered node supporting Wake-Up communication sends a Wake Up Notification Command to get attention when it is awake and receives a Wake Up No More Information Command when it can safely return to sleep.

- RT:00.12.0004.1 A battery powered Z-Wave Plus node supporting Wake-Up communication SHOULD implement a timeout mechanism which makes the node return to sleep if the node does not receive a Wake Up No More Information Command.
- RT:00.11.0021.2 If no Wake Up No More Information Command is received from the Wake Up destination, the node MUST respond to the Wake Up destination until 10 seconds have elapsed since the last transmission or reception of an application frame supported by the node, a NOP frame or a Request Node Info Frame with the Wake Up destination.

An illustration is given in Figure 12

RT:00.13.0004.1

<sup>© 2021</sup> Z-Wave Alliance, Inc. All Rights Reserved. This document may only be copied and distributed internally.



Figure 12, Wake Up Command Class

#### 3.9 Network maintenance

RT:00.12.0005.1 The network rediscovery (Request neighbor update) feature SHOULD only be used as last resort in case the runtime communication fails.

#### 3.10 SmartStart requirements

#### 3.10.1 Support requirements

#### 3.10.1.1 SmartStart learn mode activation

- RT:00.11.0023.1 A node supporting SmartStart inclusion MUST enter SmartStart Learn Mode by default when ready after powering up, regardless of network inclusion status.
- RT:00.11.0024.1 A node supporting SmartStart inclusion MUST fall back on SmartStart Learn Mode after deactivating Learn Mode.

#### 3.10.1.2 Higher Inclusion Request Interval

If a very power-constrained battery node is designed to settle at a higher Max Inclusion RequestRT:00.11.0025.1Interval (aNwkSmartStartMaxInclusionRequestInterval in [12]) than the default 512 seconds, this valueMUST be advertised in the node's provisioning information (QR Code, refer to [1] and [9]).

#### 3.10.2 Control requirements

RT:00.11.002B.1 A controller providing control of the SmartStart functionality is NOT REQUIRED to support the SmartStart functionality and support being included in a network using SmartStart inclusion.

#### 3.10.2.1 Command Class support

- RT:00.11.002E.2 A Z/IP Gateway providing the SmartStart functionality MUST support the following Command Classes on the IP side:
  - Network Management Inclusion Command Class, version 3 or newer
- RT:00.12.0009.1 A Z/IP Gateway providing the SmartStart functionality SHOULD support the following Command Classes on the IP side:
  - Node Provisioning Command Class

#### 3.10.2.2 User interface

- RT:00.11.0032.2 A controller providing control of the SmartStart functionality MUST:
  - provide a method for the end user to view the Node Provisioning List entries with their network inclusion status (included/ not included or failed).
  - provide a method for the end user to manually add and remove entries in the Node Provisioning List.
  - Provide a method for the end user to edit available settings for each entry in the Node Provisioning List. (e.g., Inclusion setting, Advanced joining)
  - support S2 inclusion with authentication using the DSK PIN code.

RT:00.11.0033.1 If a user removes a node from the Node Provisioning List and the node is still included in the Z-Wave network, the controller MUST inform the end user that the node will stay in the network and requires to be excluded manually or reset to factory default in order to leave the Z-Wave Network.

RT:00.11.0034.1 A controller MUST inform the end user that S2 only (non-SmartStart) nodes present in the Provisioning List require to perform a classic inclusion to add them into the Z-Wave network.

#### 3.10.2.3 QR Code scanning capability

- RT:00.12.0006.1 A controller providing the SmartStart functionality SHOULD provide a QR Code scanning capability.
   If the controller offers a QR Code scanning capability:
   RT:00.11.0035.1
   It MUST support the addition of nodes using QR Code format defined in [10] in its Provisioning
- List when scanning the QR Code.
   It SHOULD support scanning of S2 only QR codes representing the DSK String prefixed with "Tws2dsk:" (example: "Tws2dsk:34028-23669-20938-46346-33746-07431-56821-14553") in

"zws2dsk:".(example: "zws2dsk:34028-23669-20938-46346-33746-07431-56821-14553") in order to simplify the S2 bootstrapping process.

## 4 ROLE TYPE OVERVIEW

Z-Wave Role Types is used as part of the Z-Wave Plus certification program. Role types define how battery and network functionalities must be implemented. This is to provide better uniformity and hence ensuring better interoperability between Z-Wave Plus devices.

Role types are backwards compatible with Z-Wave products certified under earlier certification programs.

The Role Types are device specific and hence the Device Type will define which Role Type(s) a given device can support.

Table 1 shows an overview of Role Types which are described in details in Chapter 5.

Role Type	Abbre- viation	Repea- ter	Power source	Can be SIS	Network setup	Setup lifeline	Report through lifeline	Direct controlable	Heart beat comms.
Central Static Controller	CSC	1	Mains	1	1	1	1	1	X
Sub Static Controller	SSC	1	Mains	X	1	X	1	1	X
Portable Controller	РС	X	Battery	X	1	X	1	X	X
Reporting Portable Controller	RPC	X	Battery	X	1	X	1	X	~
Portable Slave	PS	X	Battery	X	X	X	~	X	X
Always On Slave	AOS	1	Mains	X	X	X	1	1	X
Listening Sleeping Slave	LSS	X	Battery	X	X	X	1	1	X
Reporting Sleeping Slave	RSS	X	Battery	X	X	X	1	X	~
Network Aware Slave	NAS	1	Mains	X	X	X	1	1	X

#### Table 1, Overview of Role Types

The following functionalities depend on the actual Role Type:

**Repeater:** Indicates whether the device can act as repeater in the network. This requires an always listening device, which can accommodate any routing requests immediately.

**Power source:** Mains powered devices are accessible immediately and are always listening devices. Battery powered devices focus on battery lifetime extension as one of the primary objectives.

**Can be SIS:** The nodde supports the Static Update Controller (SUC) and SUC node ID Server (SIS) functions. When SIS functionality is enabled, the controller also takes the Primary Controller role. All

other controllers operate as Inclusion Controllers, i.e. they can request that nodes are included/excluded.

If a SIS is present in the network, it is RECOMMENDED that all other devices update their network topology once a day and before configuring associations.

**Network setup:** The node is capable of managing the network and inclusion/exclusion of nodes.

Setup lifeline: The node is able to configure lifeline associations.

**Report through lifeline:** The node MUST be able to report events via a lifeline association to a central home control application.

**Direct controllable:** Mains powered devices and battery devices configured as Frequently Listening Routing Slave (FLiRS) can be controlled at any time.

**Heart beat communication:** Operating as a sleeping device, the node is able to connect at given intervals to a central home control application to allow delivery of messages from other devices. Such a node supports the Wake Up Command Class.

#### 4.1 Detecting the Role Type of a device

RT:00.11.0036.1

The Role Type of a node can be requested via the Z-Wave Plus Info Command Class, which MUST be listed as the first supported Command Class in the Node Information Frame (NIF) by all Z-Wave Plus nodes. For details about Z-Wave Plus Info Command Class, refer to [4].

Role Type	Value	Identifiers
Central Static Controller (CSC)	0x00	ROLE_TYPE_CONTROLLER_CENTRAL_STATIC
Sub Static Controller (SSC)	0x01	ROLE_TYPE_CONTROLLER_SUB_STATIC
Portable Controller (PC)	0x02	ROLE_TYPE_CONTROLLER_PORTABLE
Reporting Portable Controller (RPC)	0x03	ROLE_TYPE_CONTROLLER_PORTABLE_REPORTING
Portable Slave (PS)	0x04	ROLE_TYPE_SLAVE_PORTABLE
Always On Slave (AOS)	0x05	ROLE_TYPE_SLAVE_ALWAYS_ON
Reporting Sleeping Slave (RSS)	0x06	ROLE_TYPE_SLAVE_SLEEPING_REPORTING
Listening Sleeping Slave (LSS)	0x07	ROLE_TYPE_SLAVE_SLEEPING_LISTENING
Network Aware Slave (NAS)	0x08	ROLE_TYPE_SLAVE_NETWORK_AWARE

#### Table 2, Role Type identifiers

## 5 ROLE TYPE DEFINITIONS

The following sections describe requirements for individual Role Types. Each Role Type has requirements categorized in the following subsections:

- 1. **Protocol Requirements**
- 2. Setup
- 3. **Runtime Configuration**
- 4. **Runtime Communication**

The Setup subsection describes the specific requirements for a given Role Type during and after a network inclusion. Figure 13 shows the different steps of a node setup / commissioning.



Figure 13, Node Setup / commissioning

#### **Network inclusion**

The network inclusion process is described in Appendix A. Additional recommendations are given for the different Roles Types.

#### (S0/S2) Security bootstrapping

The security (Security 0 or Security 2) bootstrapping takes place immediately after the network inclusion. Refer to [5].

#### **Discover supported Command Classes**

The controlling node reads the supported command classes before interviewing each of them.

#### **Command Class interview**

Each role type specifies some requirements that must be observed during the Command Class interview:

#### • Lifeline configuration:

When interviewing the Association or Multi channel association Command Class, the including controller sets up the lifeline association if it is the SIS.

RT:00.11.0037.1

If a SIS is present in the network, the destination NodeID of the Lifeline group MUST be the SIS NodeID. Requirements are detailed for each Role Type in the following sections. Refer to [1] and [2] for Lifeline group definition

#### • Battery considerations

Some requirements apply for battery powered nodes, supporting the Wake Up Command Class. Details are given for each Role Type.

#### Commissioning and runtime phases

The commissioning phase is defined as the period after a node's inclusion during which the Security bootstrapping, Lifeline configuration, Wake Up configuration and initial device interview is made by a controller.

RT:00.12.0008.1 It is RECOMMENDED that a controller does not display a newly included node as ready to be operated during the commissioning phase.

The commissioning phase is considered over when the initial interview is completed or latest 10 minutes after the network inclusion.

Once the commissioning phase is over, a node is said to be in the runtime phase.

#### 5.1 Central Static Controller (CSC)

The Central Static Controller Role Type is intended for always powered devices which are capable of operating as a central controller. The CSC will be the central device for most network communications and other devices will rely on it for unsolicited information via the lifeline association to the CSC (which is also the SIS). This will enable the user to receive key information without having to perform major network configuration tasks.

The CSC is typically a router, central gateway or some sort of central communication panel.

#### 5.1.1 CSC Protocol Requirements

RT:01.11.0001.1	The CSC MUST respect requirements described in chapter 3.
RT:01.11.0002.1	The CSC MUST support the Static Update Controller (SUC) and SUC node ID Server (SIS) functions.
RT:01.11.0003.1	The CSC MUST be mains powered and MAY have a battery back-up.
RT:01.11.0004.1	The CSC MUST set the listening flag to 1 in its NIF.
RT:01.11.0005.1	The CSC MUST support and control the S0 and S2 Command Classes.
RT:01.11.0006.2	The CSC MUST support the following network roles:

- SIS
- Secondary controller (if Learn Mode is supported)
- Inclusion controller (if Learn Mode is supported)

#### 5.1.1.1 If first node in the network

- RT:01.11.0007.3 If the CSC is the first node in the network, it MUST set itself the SIS role and MUST support the following network functions:
  - Include new nodes ("Add mode")
  - Exclude nodes
  - Remove failing nodes
- RT:01.13.0001.2 Additionally, it MAY support the following network function:
  - Replace failing nodes
  - Learn Mode
- RT:01.11.0008.1 It MUST NOT be possible to activate Learn Mode if the CSC is the SIS and other nodes are included in the network.

#### 5.1.2 CSC Setup

#### 5.1.2.1 Inclusion process

RT:01.12.0001.1 It is RECOMMENDED to use soft buttons for activating learn mode and add mode on a CSC Role Type.

#### 5.1.2.2 Lifeline configuration

When including a node,

 if the CSC is the SIS: it MUST set itself as the Association group ID 1 (Lifeline) destination. if the CSC is not the SIS: it MAY set the SIS' NodeID as the Association group ID 1 (Lifeline) RT:01.13.0003.1 destination. The CSC MUST assign a return route for the SIS after setting the lifeline of Slave Role Types. RT:01.11.0016.1 Details and requirements about establishing the Lifeline are provided in the Association and Multi Channel Association control specifications [11]. 5.1.2.3 CSC including a SSC, PC, RPC or NAS **Battery considerations** If the CSC is the SIS and the included node is of Role Type RPC: RT:01.11.000A.1 • The CSC MUST configure the Wake Up Interval Set Command destination NodeID to its NodeID. RT:01.11.000B.1 The CSC MUST send a Wake Up No More Information Command when the CSC has no more • command to transmit. 5.1.2.4 CSC including a PS, LSS or RSS **Battery considerations** If the CSC is the SIS and the included node is of Role Type PS or RSS, the CSC MUST: RT:01.11.000D.1 • configure the Wake Up Interval Set Command destination NodeID to its NodeID. send a Wake Up No More Information Command when the CSC has no more command to transmit. If the CSC is the SIS and the included node is of Role Type PS: • If the node advertises Wake-Up Capabilities (Wake-Up Command Class, version 2 or newer), the RT:01.11.000E.1 Wake Up Interval Set Command Seconds field MUST be within the allowed range If the CSC is not the SIS, it SHOULD NOT send a Wake Up Interval Set Command to the included node. RT:01.12.0002.1 If the CSC is not the SIS and sends a Wake Up Interval Set Command, the destination NodeID MUST be RT:01.11.0010.1 the SIS' NodeID. 5.1.2.5 **CSC** including an AOS

Z-Wave Plus Role Type Specification

#### **Battery considerations**

None

#### 5.1.2.6 CSC including another CSC

RT:01.11.0013.1 If the CSC is included by another CSC, the included CSC MUST take the Inclusion Controller role and MUST support the following network functions:

- Include new nodes ("Add mode")
- Exclude nodes
- Learn mode
- Remove failing node

RT:01.13.0002.1 Additionally, it MAY support the following network function:

• Replace failing node

#### **Battery considerations**

None

#### 5.1.2.7 CSC included by a PC, RPC, SSC

RT:01.11.0014.1 The CSC MUST accept to take the SIS role when a PC, RPC or SSC assigns it to the included CSC.

#### Lifeline configuration

RT:01.12.0003.1 If the CSC was assigned the SIS role, previously added nodes may have no lifeline associations. The CSC SHOULD create lifeline associations in all existing nodes that are directly reachable.

#### **Battery considerations**

None

#### 5.1.3 CSC Runtime Configuration

RT:01.11.0015.1 The CSC MUST instruct a reporting node (RPC, RSS, PS) to return to sleep after application data has been delivered to the node. This is done by sending a Wake Up No More Information Command. An illustration is given in Figure 12.

#### 5.1.4 CSC Runtime Communication

No requirements

#### 5.2 Sub Static Controller (SSC)

The Sub Static Controller Role Type is intended for static controllers which are not suitable as central controllers. It is aimed at applications that require a static controller to manage a subset of nodes. It is typically offered as a bundled package with e.g. sensors.

#### 5.2.1 SSC Protocol Requirements

RT:02.11.0001.1	The SSC MUST respect requirements described in chapter 3
RT:02.11.0002.1	The SSC MUST be mains powered and MAY have a battery back-up.
RT:02.11.0003.1	The SSC MUST set the listening flag to 1 in its NIF.
RT:02.11.0004.1	The SSC MUST NOT support the SIS functionality.
RT:02.12.0001.1	The SSC SHOULD NOT configure lifeline associations.
RT:02.11.0005.1	The SSC MUST support the following network roles:

- Primary controller
- Secondary controller
- Inclusion controller

#### 5.2.1.1 If first node in the network

RT:02.11.0006.1	If the SSC is the first node in the network, it MUST take the Primary Controller role and MUST support
	the following network functions:

- Include new nodes ("Add mode")
- Exclude nodes
- Learn mode
- RT:02.11.0007.1 It MUST NOT be possible to activate Learn Mode if the SSC is the Primary Controller and other nodes are included in the network.

#### 5.2.2 SSC Setup

#### 5.2.2.1 Inclusion process

RT:02.12.0002.1 It is RECOMMENDED to use a physical push button for activating learn mode and a soft button for activating add mode on a SSC Role Type.

#### 5.2.2.2 Lifeline configuration

No requirement.

#### 5.2.2.3 SSC including a CSC

RT:02.11.0008.1 If the SSC is the Primary Controller and a CSC is added to the network, the SSC MUST assign the SIS role to the CSC.

RT:02.13.0001.1 If the SSC is the Primary Controller and has previously included some Wake Up nodes, it MAY re-assign the Wake Up destination NodeID to the CSC/SIS for the previously included Wake Up nodes at the next Wake Up Notification.

#### RT:02.11.0009.1 The SSC becomes an inclusion controller and MUST support the following network functions:

- Include new nodes ("Add mode")
- Exclude nodes
- Learn mode

#### **Battery considerations**

None

#### 5.2.2.4 SSC including an RPC, PS or RSS

#### **Battery considerations**

- RT:02.12.0003.1If there is a SIS in the network, the SSC SHOULD NOT send a Wake Up Interval Set Command to the<br/>included node. If there is a SIS in a network and the SSC sends a Wake Up Interval Set Command, the<br/>destination NodeID MUST be the SIS' NodeID.
- RT:02.12.0004.1If there is no SIS present in the network, the SSC SHOULD send a Wake Up Interval Set Command withRT:02.11.000B.1its own NodeID as destination. If issuing a Wake Up interval Set Command, the SSC MUST respect the<br/>following rules:
  - If the included node is of Role Type RPC, PS or RSS:
  - The SSC SHOULD set the Wake Up Interval Set Command Seconds field to the default Wake Up time advertised by the included node.
  - If the included node is of Role Type PS:

RT:02.11.000C.1

RT:02.12.0005.1

• If the node advertises Wake-Up Capabilities (Wake-Up Command Class, version 2 or newer), the Wake Up Interval Set Command Seconds field MUST be within the allowed range.

#### 5.2.2.5 SSC including an SSC, PC, AOS, LSS or NAS

#### **Battery considerations**

None

#### 5.2.3 SSC Runtime Configuration

No requirements

#### 5.2.4 SSC Runtime communication

No requirements

© 2021 Z-Wave Alliance, Inc. All Rights Reserved. This document may only be copied and distributed internally.

#### 5.3 Portable Controller (PC)

The Portable Controller Role Type is intended for portable controllers that can setup and maintain a Z-Wave network but do not require unsolicited reporting. It is typically used by home control remotes that control a few lights.

#### 5.3.1 PC Protocol Requirements

RT:03.11.0001.1	The PC MUST respect requirements described in chapter 3
RT:03.11.0002.1	The PC MUST be battery powered and support the Battery Command Class.
RT:03.11.0003.1	The PC MUST set the listening flag to 0 in its NIF.
RT:03.12.0001.1	The PC SHOULD NOT configure lifeline associations when adding nodes to the network.
RT 03 11 0004 1	The PC MUST support the following network roles:

- Primary controller
- Secondary controller
- Inclusion controller

#### 5.3.1.1 If first node in the network

- RT:03.11.0005.1 If the PC is the first node in the network, it MUST take the Primary Controller role and MUST support the following network functions:
  - Include new nodes ("Add mode")
  - Exclude nodes
  - Learn mode
- RT:03.11.0006.1 It MUST NOT be possible to activate Learn Mode if the PC is the Primary Controller and other nodes are included in the network.

#### 5.3.2 PC Setup

#### 5.3.2.1 Inclusion process

RT:03.12.0002.1 It is RECOMMENDED to use physical push buttons for activating learn mode and add mode on a PC Role Type.

#### 5.3.2.2 Lifeline configuration

No requirement.

#### 5.3.2.3 PC including a CSC

RT:03.11.0007.1 If the PC is the Primary Controller and a CSC is added to the network, the PC MUST assign the SIS role to the CSC.

- RT:03.11.0008.1 The PC becomes an inclusion controller and MUST support the following network functions:
  - Include new nodes ("Add mode")
  - Exclude nodes
  - Learn mode

#### **Battery considerations**

None

#### 5.3.2.4 PC including an RPC, PS or RSS

#### **Battery considerations**

None.

#### 5.3.2.5 PC including an SSC, PC, AOS, LSS or NAS

#### **Battery considerations**

None

#### 5.3.3 PC Runtime Configuration

No requirements

#### 5.3.4 PC Runtime communication

No requirements

#### 5.4 Reporting Portable Controller (RPC)

The Reporting Portable Controller Role Type is intended for portable reporting controllers, which need to setup a Z-Wave network and also send unsolicited messages.

The RPC Role Type may for instance be used for a battery powered thermostat which can include and exclude nodes in a small network. In addition, the thermostat may be configured remotely.

#### 5.4.1 RPC Protocol Requirements

RT:04.11.0001.1 RT:04.11.0002.1	<ul> <li>The RPC MUST respect requirements described in chapter 3.</li> <li>The RPC MUST be battery powered and support the following Command Classes:</li> <li>Battery Command Class</li> <li>Wake Up Command Class version 2 or newer</li> </ul>
RT:04.11.0003.1 RT:04.12.0001.1	<ul> <li>Wake Op command class, version 2 of newer</li> <li>The RPC MUST set the listening flag to 0 in its NIF.</li> <li>The RPC SHOULD NOT configure lifeline associations when adding nodes to the network.</li> </ul>
RT:04.11.0004.1	The RPC MUST support the following network roles:
	Primary controller

- Secondary controller
- Inclusion controller

#### 5.4.1.1 If first node in the network

- RT:04.11.0005.1 If the RPC is the first node in the network, it MUST take the Primary Controller role and MUST support the following network functions:
  - Include new nodes ("Add mode")
  - Exclude nodes
  - Learn mode
- RT:04.11.0006.1 It MUST NOT be possible to activate Learn Mode if the RPC is the Primary Controller and other nodes are included in the network.

#### 5.4.2 RPC Setup

#### 5.4.2.1 Inclusion process

RT:04.12.0002.1 It is RECOMMENDED to use physical push buttons for activating learn mode and add mode on an RPC Role Type.

#### 5.4.2.2 Lifeline configuration

RT:04.13.0001.1 When including a node, if a SIS is present in the network, the RPC MAY set the SIS' NodeID as the Association group ID 1 (Lifeline) destination.

Details and requirements about establishing the Lifeline are provided in the Association and Multi Channel Association control specifications [11].

#### 5.4.2.3 RPC including a CSC

RT:04.11.0007.1 If the RPC is the Primary Controller and a CSC is added to the network, the RPC MUST assign the SIS role to the CSC.

- RT:04.11.0008.1 The RPC becomes an inclusion controller and MUST support the following network functions:
  - Include new nodes ("Add mode")
  - Exclude nodes
  - Learn mode

#### **Battery considerations**

None

#### 5.4.2.4 RPC Including an RPC, PS or RSS

#### **Battery considerations**

None

#### 5.4.2.5 RPC including an SSC, PC, AOS, LSS or NAS

#### **Battery considerations**

None

#### 5.4.3 RPC runtime configuration

- RT:04.11.0009.1 The RPC MUST support the Wake Up Command Class as described in 0.
- RT:04.12.0005.1 The RPC SHOULD have a physical push button for waking up the device for expedited communication. This enables interactive delivery of new configuration parameters or firmware updates.
- RT:04.11.000A.1 The RPC MUST implement a Minimum Wake Up Interval in the range 0 ..4200 (i.e. between 0 second and 70 minutes).
- RT:04.11.000B.1 If the RPC's Minimum Wake Up Interval is 0, the RPC MUST implement a Maximum Wake Up Interval greater than 0.

#### 5.4.4 RPC runtime communication

RT:04.11.000C.1 The RPC MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for more details.

#### 5.5 Portable Slave (PS)

The Portable Slave Role Type is intended for battery powered devices that aim for the lowest possible power consumption. The PS only wakes up in response to a physical event such as a button press. The PS allows for optimal cost, as no EEPROM is required.

#### 5.5.1 PS Protocol Requirements

RT:05.11.0001.1 The PS MUST respect requirements described in chapter 3

The PS MUST be battery powered and support the following Command Classes:

- Battery Command Class
- Wake Up Command Class, version 2 or newer
- RT:05.11.0003.1 The PS MUST set the listening flag to 0 in its NIF.

The PS can only be added to a network and has no network role requirement.

#### 5.5.2 PS Setup

RT:05.11.0002.1

The setups of a PS by a CSC, SSC, PC or RPC are respectively described in 5.1.2.4, 5.2.2.4, 5.3.2.4 or 5.4.2.4. The PS has no additional requirement when being included.

#### 5.5.2.1 Inclusion process

RT:05.12.0001.1 It is RECOMMENDED to use a physical push button for activating learn mode on a PS Role Type.

#### 5.5.3 PS Runtime configuration

- RT:05.11.0004.1 The PS MUST support the Wake Up Command Class as described in 0.
- RT:05.12.0002.1 The PS SHOULD use a default Wake-Up interval of 0.
- RT:05.12.0003.1 The PS SHOULD have a physical push button for waking up the device for expedited communication. This enables interactive delivery of new configuration parameters or firmware updates.

#### 5.5.4 PS Runtime communication

RT:05.11.0005.1 The PS MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for more details.

#### 5.6 Always On Slave (AOS)

The Always On Slave Role Type is intended for mains powered devices that are always reachable. One example of such a device is a light switch.

#### 5.6.1 AOS Protocol Requirements

RT:06.11.0001.1The AOS MUST respect requirements described in chapter 3RT:06.11.0002.1The AOS MUST be mains powered and MAY have a battery back-up.RT:06.11.0003.1The AOS MUST set the listening flag to 1 in its NIF.The AOS can only be added to a network and has no<br/>network role requirement.

#### 5.6.2 AOS Setup

The setups of an AOS by a CSC, SSC, PC or RPC are respectively described in 5.1.2.5, 5.2.2.5, 5.3.2.5 or 5.4.2.5. The AOS has no additional requirement when being included.

#### 5.6.2.1 Inclusion process

RT:06.12.0001.1 It is RECOMMENDED to use a physical push button for activating learn mode on an AOS Role Type.

#### 5.6.3 AOS Runtime Configuration

AOS can always be configured, as it is always listening.

#### 5.6.4 AOS Runtime communication

RT:06.11.0004.1 The AOS MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for more details.

#### 5.7 Reporting Sleeping Slave (RSS)

The Reporting Sleeping Slave Role Type is intended for battery-powered devices that only wake up and communicates when an event has occurred. This allows to reconfigure the device remotely. Examples include sensors, wall controllers etc.

#### 5.7.1 RSS Protocol Requirements

RT:07.11.0001.1 The RSS MUST respect requirements described in chapter 3.

The RSS MUST be battery powered and support the following Command Classes:

- Battery Command Class
- Wake Up Command Class, version 2 or newer
- RT:07.11.0003.1 The RSS MUST set the listening flag to 0 in its NIF.

The RSS can only be added to a network and has no network role requirement.

#### 5.7.2 RSS Setup

RT:07.11.0002.1

The setups of an RSS by a CSC, SSC, PC or RPC are respectively described in 5.1.2.4, 5.2.2.4, 5.3.2.4 or 5.4.2.4. The RSS has no additional requirement when being included.

#### 5.7.2.1 Inclusion process

RT:07.12.0001.1 It is RECOMMENDED to use a physical push button for activating learn mode on an RSS Role Type.

#### 5.7.3 RSS Runtime configuration

- RT:07.11.0004.1 The RSS MUST support the Wake Up Command Class as described in 0 and in Figure 12.
- RT:07.12.0002.1 The device SHOULD have a physical push button for waking up the device for expedited communication. This enables interactive delivery of new configuration parameters or firmware updates.
- RT:07.11.0005.1 The RSS MUST implement a Minimum Wake Up Interval in the range 0 ..4200 (i.e. between 0 second and 70 minutes).
- RT:07.11.0006.1 If the RSS's Minimum Wake Up Interval is 0, the RSS MUST implement a Maximum Wake Up Interval greater than 0.

#### 5.7.4 RSS Runtime communication

RT:07.11.0007.1 The RSS MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for details.

#### 5.8 Listening Sleeping Slave (LSS)

The Listening Sleeping Slave Role Type is intended for battery-operated devices that can be reached even though they are sleeping thanks to Beaming (FLIRS devices). Examples include Door Locks and Battery operated Thermostats.

#### 5.8.1 LSS Protocol Requirements

RT:08.11.0001.1The LSS MUST respect requirements described in chapter 3.RT:08.11.0002.1The LSS MUST be battery powered and support the Battery Command Class.RT:08.11.0003.1The LSS MUST set the listening flag to 0 in its NIF.

The LSS can only be added to a network and has no network role requirement

#### 5.8.2 LSS Setup

The setups of an LSS by a CSC, SSC, PC or RPC are respectively described in 5.1.2.4, 5.2.2.4, 5.3.2.4 or 5.4.2.4. The LSS has no additional requirement when being included.

#### 5.8.2.1 Inclusion process

RT:08.12.0001.1 It is RECOMMENDED to use a physical push button for activating learn mode on a LSS Role Type.

#### 5.8.3 LSS Runtime configuration

A LSS can always be configured, as it is reachable via FLiRS communication.

#### 5.8.4 LSS Runtime communication

- RT:08.11.0004.1 The LSS MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for details.
- RT:08.11.0005.1 The LSS MUST stay awake for at least 2 seconds after communicating.

#### 5.9 Network Aware Slave (NAS)

The Network Aware Slave Role Type is intended for slaves with application controlling capabilities, which are leveraging controller functionalities to be aware of the network topology and nodes capabilities.

The SIS (or primary controller) will consider a NAS as a controller, but the NAS will not be able to include new nodes in the network.

#### 5.9.1 NAS Protocol Requirements

RT:09.11.0001.1	The NAS MUST respect requirements described in chapter 3.
RT:09.11.0002.1	The NAS MUST be mains powered and MAY have a battery back-up.
RT:09.11.0003.1	The NAS MUST set the listening flag to 1 in its NIF.
RT:09.11.0006.1	The NAS can only be added to a network and MUST take the inclusion controller or the secondary
	controller role when added to a network.

RT:09.11.0004.1 The NAS MUST NOT provide the following network functions:

- Include new nodes
- Exclude nodes
- Remove failing node
- Replace failing node

#### 5.9.2 NAS Setup

The setups of an NAS by a CSC, SSC, PC or RPC are respectively described in 5.1.2.3, 5.2.2.5, 5.3.2.5 or 5.4.2.5. The NAS has no additional requirement when being included.

#### 5.9.2.1 Inclusion process

RT:09.12.0001.1 It is RECOMMENDED to use a physical push button for activating learn mode on an NAS Role Type.

#### 5.9.3 NAS Runtime Configuration

The NAS can always be configured, as it is always listening.

#### 5.9.4 NAS Runtime communication

RT:09.11.0005.1 The NAS MUST communicate via the lifeline association if any lifeline association exists. Refer to [1] for more details.

## **APPENDIX AINCLUSION PROCESS**

This section outlines the recommended inclusion process that all Role Types should follow. The processes for both node including and being included are covered.



Figure 14, Inclusion process for the node being included



Figure 15, Inclusion process for the including node

## REFERENCES

- [1] Software Design Specification, Z-Wave Plus Device Types Specification.
- [2] Software Design Specification, Z-Wave Plus v2 Device Types Specification.
- [3] Z-Wave Application Command Class Specification
- [4] Z-Wave Management Command Class Specification
- [5] Z-Wave Transport-Encapsulation Command Class Specification
- [6] Z-Wave Network Protocol Command Class Specification
- [7] IETF RFC 2119, Key words for use in RFC's to Indicate Requirement Levels, http://tools.ietf.org/pdf/rfc2119.pdf
- [8] Software Design Specification, Z-Wave Device and Command Class Types and Defines Specification.
- [9] Node Provisioning Information Type Registry (QR code, Z/IP Gateway, Smart Start)
- [10] Node Provisioning QR Code Format (S2, Smart Start)
- [11] Z-Wave Command Class Control Specification
- [12] Z-Wave Network Layer Specification